EF40 & EF40P Series

Remote fixture



Features

- · Quality illumination requires fewer fixtures
- Clear polycarbonate UV and impact resistant lens with optional tamper-proof screws to prevent tampering.
- Easy lamp replacement
- Modern design will blend into surroundings
- Selection of die-cast or polycarbonate back plate
- · For indoor use only
- CSA certified to C22.2 No. 141-15
- · Warranty details at: www.emergi-lite.ca

Dimensions

Dimensions are approximate and subject to change.





7-3/8" [18.7 cm]	3-3/4" [9.5 cm]	
4-7/8" [12.3 cm]		

Typical specifications

Supply and install **Emergi-Lite® EF40P Series** remote emergency lighting. These remote fixtures will consist of either single or double lamp configurations as specified and include a UV resistant fire retardant polycarbonate back plate and a clear heavy-duty UV resistant polycarbonate light cover.

The remote fixture shall be certified to CSA C22.2 No. 141.

The head(s) shall be fully adjustable and be equipped with high efficiency LED lamp(s) of ______ V, _____ W.

The remote unit shall be **Emergi-Lite®** model: _____

Wire guards

Ordering code	Description
460.0029-E	Wall mount

Replacement lamps

Ordering code	Lamp type	Voltage/wattage
580.0097-E	MR16 LED	6V-4W
580.0122-E	MR16 LED	6V-5W
580.0093-E	MR16 LED	12V-4W
580.0098-E	MR16 LED	24V-4W
580.0100-E	MR16 LED	24V-6W
580.0104-E	MR16 LED	12V-5W
580.0106-E	MR16 LED	12V-6W
580.0113-E	MR16 LED	120V-4W

Housing colour







Ordering information

EF40P Series	Number of lamps	Lamp type	Colour	Lamp type/voltage/wattage	Options
EF40P= polycarbonate	Blank= one lamp	M = MR16	B = black	LA = MR16 LED, 6V-4W	Blank= no option
	D= two lamps		Blank= factory white	LB = MR16 LED, 6V-5W	T= tamper-proof screws1
			G = grey	LG = MR16 LED, 12V-4W	
				LI= MR16 LED, 12V-5W	
				LJ = MR16 LED, 12V-6W	
	_			LL = MR16 LED, 24V-4W	
Example: EF40PDMBLI					1690.0454-E= tamper-proof bit
			Other colours available		(sold separately)
EF40 Series	Number of lamps	Lamp type	Colour	Lamp type/voltage/wattage	Options
EF40= die-cast	Blank= one lamp	M = MR16	B = black	LA = MR16 LED,6V-4W	Blank= no option

EF40 Series	Number of lamps	Lamp type	Colour	Lamp type/voltage/wattage	Options
EF40= die-cast	Blank= one lamp	M = MR16	B= black	LA = MR16 LED,6V-4W	Blank= no option
	D= two lamps		Blank= factory white	LB = MR16 LED, 6V-5W	T= tamper-proof screws1
			G = grey	LG = MR16 LED, 12V-4W	
				LI= MR16 LED, 12V-5W	
				LJ = MR16 LED, 12V-6W	
				LL = MR16 LED, 24V-4W	
Example: EF40DMLI				LM = MR16 LED, 24V-6W	1690.0454-E= tamper-proof bit
Example: El 40511El			Other colours available	LW = MR16 LED, 120V-4W	(sold separately)